

VH1150

Test Hardware for CAN and LIN Conformance Tests with CANoe

What is VH1150?

- > Compact hardware device for automating ECU conformance tests
- > VH1150 is integrated in the "CANoe Test Package VAG" for High-Speed CAN tests and in LIN conformance tests
- > Application areas are test implementations based on CANoe

Overview of Advantages

- > Simple interface via USB 2.0
- > Typical voltage supply via 4 mm socket or 4-pin round connector with mechanical lock
- > Independent supply for automotive terminals IGN, V_{batt} and GND, switchable via relay. The current state is indicated by an LED immediately.
- > Program-controlled measurement of ECU current consumption for easy sleep/wake-up monitoring
- > Configurable output voltage (independent of input voltage) common to terminals IGN and V_{batt} . Overload state is indicated by an LED immediately.

Highlights

- > Ground offset of the ECU and of the LIN line
- > Limiting of the recessive level of the LIN line
- > Short circuit and open circuit options for CAN and LIN lines
- > Analog and digital I/O connections

Scope of Delivery

- > VH1150 hardware with USB interface
- > VH1150 manual
- > Installation CD
- > USB cable (2 meters)
- > Y cable

Optionally available:

- > External voltage supply
- > Termination resistor with 120 Ω (CANterm120)

More information about conformance tests:

www.vector.com/canoe_ctp



Compact VH1150 test hardware device for automating ECU conformance tests with CANoe.

Technical Data

	VH1150
External voltage supply	12...24 V (± 0.3 V accuracy), 5 A
Configurable output voltage (ECU supply voltage)	3...28 V (± 60 mV accuracy)
Max. output current (ECU current consumption)	2.5 A (input voltage >22 V)
Current measurement range	0...2.5 A (accuracy 2 % of measurement value or 0.5 mA)
Temperature range	0...40 °C
Dimensions (L x W x H)	166 x 109 x 45 mm
Weight	610 g
Ground offset: Shift in ECU ground potential Shift in LIN ground potential Accuracy	0...10 V (duration depends on ECU current) 2.5...17.5 V ± 50 mV
LIN recessive level: Adjustable limitation of the recessive level	3...28 V
CAN/LIN disturbance: CAN/LIN short circuit	CAN_H, CAN_L or LIN to GND/ V_{batt} CAN_H, CAN_L to each other
CAN/LIN open circuit (VH1150 is connected to CAN or LIN bus via Y cable)	CAN_H, CAN_L or LIN
I/O devices: DSub socket Analog input measurement range Analog output Digital input Digital output with pull-up	9-pin 0...30 V 0...15 V, ± 5 mA Switching threshold approx. 2 V Max. input current (low) 100 mA